

DO NOT THROW AWAY. STORE IN SAFE PLACE



HEIRLOOM



HEIRLOOM

Heirloom International Limited
www.heirloom.co.nz
Free Phone: 0800 434 756
Email: info@heirloom.co.nz

HEIRLOOM
BATHROOMS WITH STYLE

Heirloom **TimeKeeper**
the innovative towel
warmer timer, allowing
you to reduce your power
consumption and your
power bill!

FEATURES

- Turns towel warmer on and off twice per day with a continuous repeating cycle where the towel warmer is on 4 hours and then off 8 hours.
- The **TimeKeeper** can be retrospectively installed on existing towel warmers.
- Note: if the **TimeKeeper** is installed your towel warmer will only operate with the above continuous cycle. It cannot operate uninterrupted without an "off" cycle.

HEIRLOOM
BATHROOMS WITH STYLE



OPERATION

User Instructions

How to set your **TimeKeeper** timer to be on a repeat cycle of on for 4 hours and off for 8 hours.

Turn the towel warmer off, decide when you want the cycle to start and turn it on at that time. (For example setting it at 6pm at night turns the appliance on from 6-10pm and 6-10am everyday.)

TimeKeeper then starts counting the on hours immediately and your towel rail is now on for 4 hours at the commencement of the cycle.

To change the commencing time of the cycle, simply turn the towel warmer off and then on again at the time you now wish the on cycle to commence.

WARRANTY

TimeKeeper switches are warranted against manufacturing faults for 2 years from date of purchase. Heirloom International Limited is liable only for replacement or repair of the faulty unit and is not liable for any subsequent damages caused or costs incurred. Refer any servicing questions to the supplier you bought it from or call Heirloom International Limited on 0800 434 756.

INSTALLATION

Who should install an Heirloom **TimeKeeper**?

The Heirloom **TimeKeeper** must be installed by a registered electrician either at the same time as the towel warmer is installed or retrospectively to an existing towel warmer. Dangerous voltages (230VAC) are present on the product and in the house cabling.

No responsibility will be taken by Heirloom International Limited for damages or injury caused by incorrect installation or installation by an unqualified person/s.

Ratings

Operational voltage	100-240 VAC @ 50-60 Hz
Load capacity	3A Res. 240VAC
Operating Temp	-10°C to 30°C
Compliance	AS/NZS 3100:2002 AS/NZS CISPR 14,2002

Installation instructions

Isolate the towel rail isolation switch by switching off mains to the entire house at the fuse box.

Identify the phase (red) and neutral (black) wires from the house, and the phase (red or brown) and neutral (black or blue) coming from the towel rail element.

Attach the supplied 3 wires from the **TimeKeeper** as shown below.

Wire in the switched house phase (red) & neutral (black) cables to the corresponding red and black wires coming out of the **TimeKeeper**.

Connect the towel rail element brown wire to the brown wire coming out of the **TimeKeeper**. Connect the towel rail element blue wire to the common neutral from the house wiring (black wire). Earth wires can be connected together with a screw connector (not supplied).

Lastly carefully place the **TimeKeeper** inside the flushbox and attached the isolating switch to the wall.

